<meta name='Description' content='Suitable for signal processing of potential-free outputs, e.g. emergency stop command devices, position switches and solenoid interlocks, Suitable for signal processing of outputs connected to potentials (AOPDs), e.g. safety light grids/curtains, 3 safety contacts, STOP 0;</p>

2 safety contacts, STOP 1 (adjustable 1 ... 30 s),4 Signalling outputs,Optional: Short-circuit recognition, Manual reset with edge detection in fail-safe circuit, Automatic reset function' />

27.01.2017

13:18:07h

Datasheet - SRB324ST 24V (V.3)



Guard door monitors and Safety control modules for Emergency Stop applications / General Purpose safety controllers (Series PROTECT SRB) / SRB324ST

☑ Preferred typ



- Suitable for signal processing of potential-free outputs, e.g. emergency stop command devices, position switches and solenoid interlocks
- Suitable for signal processing of outputs connected to potentials (AOPDs), e.g. safety light grids/curtains
- 3 safety contacts, STOP 0;
- 2 safety contacts, STOP 1 (adjustable 1 ... 30 s)
- · 4 Signalling outputs
- Optional: Short-circuit recognition, Manual reset with edge detection in fail-safe circuit, Automatic reset function

(Minor differences between the printed image and the original product may exist!)

Ordering details

Product type description SRB324ST 24V (V.3)

Article number 101195504
EAN code 4030661446547

Replaced article number 101179876

eCl@ss 27-37-19-01

Approval

Approval



Classification

PL up e (STOP 0) bis d (STOP 1)

up 4 (STOP 0) Control category

bis 3 (STOP 1) 99% (STOP 0)

> 60% (STOP 1) CCF > 65 points

PFH value ≤ 2,0 x 10-8/h (STOP 0)

≤ 2,0 x 10-7/h (STOP 1)

SIL up 3 (STOP 0) bis 2 (STOP 1)

Mission time 20 Years - notice

The PFH value is applicable for the combinations listed in the table for contact load (K) (current through enabling paths) and switching cycle

number (n-op/y).

In case of 365 operating days per year and a 24-hour operation, this results in the specified switching cycle times (t-cycle) for the relay

contacts.

Diverging applications on request.

K	n-op/y	t-cycle
20 %	525.600	1,0 min
40 %	210.240	2,5 min
60 %	75.087	7,0 min
80 %	30.918	17,0 min
100 %	12.223	43,0 min

Global Properties

DC

Product name SRB324ST

Standards IEC/EN 60204-1, EN 60947-5-1, EN ISO 13849-1, IEC 61508

Compliance with the Directives (Y/N) € € Yes

Climatic stress EN 60068-2-78

Mounting snaps onto standard DIN rail to EN 60715

IEC/EN 60947-1 Terminal designations

Materials

- Material of the housings Plastic, glass-fibre reinforced thermoplastic, ventilated

- Material of the contacts , Ag-Ni, self-cleaning, positive action

Weight 435 g

Start conditions Automatic or Start button (Optional monitored)

Start input (Y/N) Yes Feedback circuit (Y/N) Yes Start-up test (Y/N) No Yes

Automatic reset function (Y/N) Reset with edge detection (Y/N) Yes

Pull-in delay

250 ms - ON delay with automatic start - ON delay with reset button 20 ms

Drop-out delay

- Drop-out delay in case of power failure 80 ms

- Drop-out delay in case of emergency stop 30 ms / ≤ 36 ms

Mechanical data

Connection type

Cable section

0,25 mm² - Min. Cable section - Max. Cable section 2.5 mm²

Pre-wired cable rigid or flexible Tightening torque for the terminals

0,6 Nm

Screw connection

Detachable terminals (Y/N) Yes

Mechanical life 10.000.000 operations

Electrical lifetime Derating curve available on request

restistance to shock 30 g / 11 ms

Resistance to vibration To EN 60068-2-6 10...55 Hz, Amplitude 0,35 mm

Ambient conditions

Ambient temperature

Min. environmental temperature
 Max. environmental temperature
 +60 °C

Storage and transport temperature

Min. Storage and transport temperature
 Max. Storage and transport temperature
 +85 °C

Protection class

Protection class-Enclosure
 Protection class-Terminals
 Protection class-Clearance

Air clearances and creepage distances To IEC/EN 60664-1

- Rated impulse withstand voltage U_{imp} 4 kV

Overvoltage categoryDegree of pollution2 To VDE 0110

Electromagnetic compatibility (EMC)

EMC rating conforming to EMC Directive

Electrical data

Rated DC voltage for controls

- Min. rated DC voltage for controls- Max. rated DC voltage for controls28.8 V

Rated AC voltage for controls, 50 Hz

Min. rated AC voltage for controls, 50 Hz
 Max. rated AC voltage for controls, 50 Hz
 20.4 V
 26.4 V

Rated AC voltage for controls, 60 Hz

Min. rated AC voltage for controls, 60 Hz
 Max. rated AC voltage for controls, 60 Hz
 20.4 V

Contact resistance $max. 100 m\Omega$

Power consumption 3.2 W; 7.1 VA, plus signalling output

Type of actuation AC/DC

Rated operating voltage Ue 24 VDC -15% / +20%, residual ripple max. 10%

24 VAC -15% / +10%

Operating current le

Frequency range 50 Hz / 60 Hz

Electronic protection (Y/N)

Yes

Fuse rating for the operating voltage

Internal electronic trip,

tripping current F1: > 2.5 A; F2 > 50 mA

(S11 - S31), > 800 mA (x 4);

Reset after disconnection of supply voltage

Current and tension on control circuits

- S11, S12, S21, S22, S31, S32 24 VDC, Test current: 10 mA

- X1, X2 24 VDC, Start pulse: 350 mA / 15 ms - X3, X4 24 VDC, Start pulse: 130 mA / 80 ms - X4, X5 24 VDC, Start pulse: 140 mA / 15 ms

Inputs

Monitored inputs

- Short-circuit recognition (Y/N) optional - Wire breakage detection (Y/N) Yes - Earth connection detection (Y/N) Yes Number of shutters 0 piece Number of openers 2 piece

Cable length 1-channel without cross-wire detection:

> 850 m with 1.5 mm² 1400 m with 2.5 mm²

2-channel with/ without cross-wire detection

Conduction resistance max. 40 Ω

Outputs

Residual current at ambient temperature up to: - 45°C = 12 A; - 55°C = 10 - Stop category 1

 $A; -60^{\circ}C = 8 A$

Stop category

Residual current at ambient temperature up to: - 45°C = 18 A; - 55°C = 15 - Stop category 0

A: - 60°C = 12 A

Number of safety contacts 5 piece Number of auxiliary contacts 1 piece Number of signalling outputs 3 piece

Switching capacity

- Switching capacity of the safety contacts (13-14; 23-24; 33-34) max. 250 V, 8 A ohmic (inductive in case of

appropriate protective wiring)

(47-48; 57-58) max. 250 V, 6 A ohmic (inductive in case of appropriate

protective wiring)

61-62: 24 VDC / 2 A - Switching capacity of the auxiliary contacts

- Switching capacity of the signaling/diagnostic outputs Y1-Y3: 24 VDC / 100 mA, residual current: 200 mA

Fuse rating

- Protection of the safety contacts 8 A slow blow (13-14; 23-24) 6.3 A slow blow (37-38)

- Fuse rating for the auxiliary contacts 2 A slow blow

- Fuse rating for the signaling/diagnostic outputs 500 mA (Internal electronic trip F3)

Utilisation category To EN 60947-5-1 13-14, 23-24, 33-34:

AC-15: 230 V / 6 A, DC-13: 24 V / 6 A

37-38, 47-48:

AC-15: 230 V / 3 A, DC-13: 24 V / 2 A

Note on the utilisation category

Number of undelayed semi-conductor outputs with signaling function 3 piece Number of undelayed outputs with signaling function (with contact) 1 piece Number of delayed semi-conductor outputs with signaling function. 0 piece Number of delayed outputs with signalling function (with contact). 0 piece

Number of secure undelayed semi-conductor outputs with signaling

function 0 piece

Number of secure, undelayed outputs with signaling function, with contact 3 piece

Number of secure, delayed semi-conductor outputs with signaling function

0 piece

Number of secure, delayed outputs with signaling function (with contact). 2 piece

LED switching conditions display

Number of LED's

6 piece

LED switching conditions display

- The integrated LEDs indicate the following operating states.
- Position relay K2
- Position relay K3
- Position relay K1
- Position relay K4
- Supply voltage
- Internal operating voltage Ui

Miscellaneous data

Applications

Guard system



Emergency-Stop button



Pull-wire emergency stop switches



Safety light curtain



Safety sensor

Dimensions

Dimensions

- Depth

- Width - Height 45 mm

100 mm 121 mm

notice

Inductive loads (e.g. contactors, relays, etc.) are to be suppressed by means of a suitable circuit.

notice - Wiring example

2 channel control shown for a guard-door monitor with two contacts, of which at least one contact has positive break, with external reset button (R).

Relay outputs: Suitable for 2 channel control, for increase in capacity or number of contacts by means of contactors or relays with positive-guided contacts.

(H2) = Feedback circuit

The control recognises cross-short, cable break and earth leakages in the monitoring circuit.

The wiring diagram is shown with guard doors closed and in de-energised condition.

Documents

Operating instructions and Declaration of conformity (pt) 622 kB, 07.10.2016

Code: mrl_srb_324st_v3_pt

Operating instructions and Declaration of conformity (es) 620 kB, 07.10.2016

Code: mrl_srb_324st_v3_es

Operating instructions and Declaration of conformity (jp) 867 kB, 20.01.2017

Code: mrl_srb_324st_v3_jp

Operating instructions and Declaration of conformity (pl) 612 kB, 11.01.2017

Code: mrl_srb_324st_v3_pl

Operating instructions and Declaration of conformity (cn) 770 kB, 13.07.2015

Code: mrl_srb_324st_v3_cn

Operating instructions and Declaration of conformity (de) 674 kB, 09.09.2016

Code: mrl_srb_324st_v3_de

Operating instructions and Declaration of conformity (da) 592 kB, 13.10.2015

Code: mrl_srb_324st_v3_da

Operating instructions and Declaration of conformity (fr) 621 kB, 07.10.2016

Code: mrl_srb_324st_v3_fr

Operating instructions and Declaration of conformity (en) 682 kB, 09.09.2016

Code: mrl_srb_324st_v3_en

Operating instructions and Declaration of conformity (it) 618 kB, 07.10.2016

Code: mrl_srb_324st_v3_it

Operating instructions and Declaration of conformity (it) 1 MB, 03.01.2012

Code: mrl_srb_324st_v3_it

Operating instructions and Declaration of conformity (nl) 620 kB, 07.10.2016

Code: mrl_srb_324st_V3_nl


Wiring example (99) 21 kB, 04.08.2008

Code: ksrb3l10

TÜV certification (de, en) 226 kB, 04.09.2012

Code: z_srbp02

Images



Wiring example

K.A. Schmersal GmbH & Co. KG, Möddinghofe 30, D-42279 Wuppertal The data and values have been checked throroughly. Technical modifications and errors excepted. Generiert am 27.01.2017 - 13:18:07h Kasbase 3.2.6.F.64I